

AD01302




Applications

- RF/IF Signal Sampling
- High-speed Analog signal Sampling

Summary

The XRM2-ADC-S11 is an XRM2 I/O Module, providing one Analog to Digital converter with 12-bit resolution and sampling rates up to 2000Mps (2500Mps with order code option /25).

Aimed at IF/RF Signal Sampling, the sampling clock can be sourced from either an external clock source or from a clock generated within the attached FPGA board. A programmable input attenuator can be used to vary the full scale input level over a 15 dB range. An Auxiliary I/O port is provided for use as a trigger input and general purpose signaling. The XRM2 communicates to the FPGA via a JESD204B high speed interface.



Deliverables

XRM2-ADC-S11 Board
One Year Warranty
One Year Technical Support

Board Format

Alpha Data XRM2 I/O Module
Input/Output Interfaces

ADC

Single Analog to Digital Converter
Resolution: 12-bit
Max Sample Freq: 2000Mps (2500Mps with ordering option)
Bandwidth: (-3dB) 10MHz to 3000MHz
Impedance: 50Ω
Connector: SMA

External clock input
External clock input

Auxiliary I/O
Auxiliary I/O

Environmental Specification

Cooling Option	Operating Temperatures		Storage Temperatures	
	Min	Max	Min	Max
AC1	-40°C	70°C	-55°C	100°C

Operating Humidity

Up to 95% (non-condensing)

EMC Standards

FCC 47CFR Part 2
EN55022:2010 Equipment ClassB

Ordering Information

Order Code: XRM2-ADC-S11(sp)

Option	Code	Description of Options
Sampling Speed	sp	blank = 2000Mps, /25 = 2500Mps

UK Office

Address: Suite L4A, 160 Dundee Street,
Edinburgh, EH11 1DQ, UK
Telephone: +44 131 558 2600
Fax: +44 131 558 2700
email: sales@alpha-data.com

USA Office

611 Corporate Circle, Suite H
Golden, CO 80401
(303) 954 8768
(866) 820 9956 - toll free
sales@alpha-data.com