


AD01252



Prime Application

IF/Baseband Signal Sampling

Summary

The XRM2-ADC-D10/250 is an XRM2 I/O Module, providing two Analog to Digital converters with 16-bit resolution at sampling rates up to 250Mps.

Aimed at IF/Baseband Signal Sampling, the sampling clock can be sourced from either an external clock source or from a clock generated within the attached FPGA board. An Auxiliary I/O port is provided for use as a trigger input and general purpose signaling. An additional two ports are available for use as high-speed interconnect between boards for synchronisation.

Deliverables

XRM2-ADC-D10/250 Board
One Year Warranty
One Year Technical Support

Board Features

- Dual 16-bit 250Mps ADCs
- External Clock Input

Board Format

Alpha Data XRM2 I/O Module

Input/Output Interfaces

ADC

Dual Analog to Digital Converters

Resolution: 16-bit
Max Sample Freq: 250Mps
Bandwidth: 4.5MHz to 700MHz
Impedance: 50Ω
Connector: SSMC

External clock input

External clock input

Auxiliary I/O

Auxiliary I/O

Synchronisation I/O

Synchronisation I/O

Environmental Specification

Cooling Option	Operating Temperatures		Storage Temperatures	
	Min	Max	Min	Max
AC0	0°C	55°C	-40°C	85°C

Operating Humidity

Up to 95% (non-condensing)

EMC Standards

FCC 47CFR Part 2
EN55022:2010 Equipment ClassB

Ordering Information

Order Code: XRM2-ADC-D10/250

UK Office

Address: Suite L4A, 160 Dundee Street,
Edinburgh, EH11 1DQ, UK
Telephone: +44 131 558 2600
Fax: +44 131 558 2700
email: sales@alpha-data.com

USA Office

611 Corporate Circle, Suite H
Golden, CO 80401
(303) 954 8768
(866) 820 9956 - toll free
sales@alpha-data.com